

# Firewall settings for hosted telephony

## Firewall settings

In the firewall, all SIP-ALG/SIP-inspection must be disabled. Also make sure, that no other SIP/VoIP features are enabled.

### Incoming

From	Port	Protocol	Service
94.127.49.224/28	5060-5061	TCP/UDP	SIP/SIP TLS
94.127.49.224/28	49152-65535	UDP	RTP/RTCP
94.127.50.0/32 <sup>1</sup>	80 <sup>2</sup>	TCP	Exchange

### Outgoing

To	Port	Protocol	Service
94.127.49.0/24	80	TCP	HTTP
94.127.49.54 94.127.49.55	123	TCP/UDP	NTP
94.127.49.0/24	443	TCP	HTTPS
94.127.49.224/28	9443	TCP	HTTPS
94.127.49.224/28	5060-5061	TCP/UDP	SIP/SIP TLS
94.127.49.224/28	49152-65535	UDP	SIP/RTCP

<sup>1</sup> Only if the Exchange calendar synchronization is enabled.

<sup>2</sup> As default port 80 is used, but if it's changed to another port, that port must be opened instead.

Ring til support  
8888 7777

Se mere på  
[ipvision.dk/firewall](http://ipvision.dk/firewall)